

## Universal Programmable Controller RT1800

- ◆ 5 DIN sizes
- ◆ Two 4-digit displays plus bargraph
- ◆ Universal programmable input
- ◆ Optional remote set-point input
- ◆ PID-fuzzy auto-tuning with bumpless Auto/Manual
- ◆ Up to 4 relays and analog control output
- ◆ Retransmission analog output available
- ◆ Triple isolation
- ◆ RAMP/SOAK function
- ◆ 2-program-with-up-to-8-point pattern set point available
- ◆ Serial interface available

RT1800 is a microprocessor-based controller with universal input, analog output, and up to 4 relays (control or alarm) that may be controlled through a number of algorithms such as ON/OFF, ON/OFF heating/cooling duplex, motor-valve control, PID, and self-tuning PID. A bumpless auto-manual change-over is built in the PID algorithm. A start-on timer allows one of output relays to be time-controlled. Two displays (for the measured value and for the set point) as well as an output-control bargraph ease operator duties. Carefully protected from electromagnetic disturbances by featuring both input and output optical isolation, RT1800 is well equipped for trouble-free operation in harsh industrial conditions.

### Technical specifications

Main input		(programmable) <sup>(1)</sup>
Pt100 (w=1.385, 1.391); 3-wire		-199.9...600.0 °C [6]
Thermocouple "B"		0...1820 °C [1]
Thermocouple "E"		0...1000 °C [2]
Thermocouple "J"		0...400.0(1200) °C [6]
Thermocouple "K"		0...400.0(1200) °C [6]
Thermocouple "L"		0...800 °C [2]
Thermocouple "N"		0...1300 °C [2]
Thermocouple "R"		0...1769 °C [2]
Thermocouple "S"		0...1769 °C [2]
Thermocouple "T"		-199.9...400.0 °C [3]
Thermocouple "U"		-199.9...600.0 °C [3]
Thermocouple "D"		0...2320 °C [2]
Linear voltage -10...50 mV		-1999...9999, programmable [4]
Linear current 0(4)...20 mA		-1999...9999, programmable [2]
Input type/range selection		programmable
Input isolation		optical, 1500 VAC
Auxiliary input <sup>(2)</sup> (option)		
Signal type		0(4)...20 mA
Function		remote set point
Control outputs		(up to 2 outputs) <sup>(3)</sup>
Relay electromechanical		3A/250V w/ NO/NC <sup>(4)</sup> contact
Solid state relay <sup>(5)</sup>		1A/250VAC
MOS gate <sup>(5)</sup>		0.1A/60V, optically isolated
Output for external SSR		24 V, 20 mA
Analog output <sup>(6)</sup>		0(4)...20 mA ( $\leq 600 \Omega$ ), 0...10 V ( $\geq 1 M\Omega$ )
Isolation		optical, 1500 VAC
Control algorithms		ON/OFF and PID-fuzzy, programmable
Auto-tuning		programmable
Auto/Manual control		bumpless, keyboard switched <sup>(7)</sup>
Pattern set point		1(2) programs w/ 16(8) points
Alarm outputs		(up to 2 outputs) <sup>(3)</sup>
Relay electromechanical		3A/250V w/ NO/NC <sup>(4)</sup> contact
Solid state relay <sup>(5)</sup>		1A/250VAC
MOS gate <sup>(5)</sup>		0.1A/60V, optically isolated
Output for external SSR		24 V, 20 mA
Retransmission output <sup>(8)</sup> (option)		
Signal type		0(4)...20 mA ( $\leq 600 \Omega$ ), 0...10 V ( $\geq 1 M\Omega$ )
Function		PV or SV transmission
Isolation		optical, 1500 VAC

<sup>(1)</sup> [n] shows the number of sub-ranges that can be selected via the keyboard.

<sup>(2)</sup> Not available with PID-fuzzy plus pattern control. For cases 'B', 'H', 'V' – instead of interface; for case 'Q' – instead of 2<sup>nd</sup> alarm output; for case 'S' – instead of interface and retransmission analog output

<sup>(3)</sup> For cases 'B', 'H', 'V' – 2 control + 2 alarm or 1 control + 3 alarm; for cases 'Q', 'S' – 1 control + 2 alarm or 2 control + 1 alarm

<sup>(4)</sup> For cases 'B', 'H', 'V' 2<sup>nd</sup> control (3<sup>rd</sup> alarm) relay is NO; for case 'Q' 2<sup>nd</sup> control (1<sup>st</sup> alarm) relay is NO; for case 'S' all relays are NO.

<sup>(5)</sup> Ask for availability!

<sup>(6)</sup> Instead of control relay!

<sup>(7)</sup> Not available for case 'S'!

<sup>(8)</sup> For cases 'H', 'V' – instead of 2<sup>nd</sup> alarm output; for case 'S' – instead of interface or 1<sup>st</sup> alarm output.

<sup>(9)</sup> For cases 'B', 'H', 'V' – instead of auxiliary input; for case 'S' – instead of retransmission or 1<sup>st</sup> alarm output.



### Serial interface <sup>(9)</sup>

Interface type	RS232 or RS485
Function	configuration and networking
Network devices	up to 31
Isolation	1500 VAC
Protocol	MODBUS ASCII or RTU
Accuracy	
Measurement error	0.3% from span
Temperature drift	0.01% from span for 1 °C
Sample time	250 ms
Cold junction compensation	automatic software
RTD line compensation	automatic software
Power supply	
Supply voltage	85...265 VAC
Consumption	max. 4 VA
Indication and controls	
Digital display	2 x 4 LED indicators
Bargraph display <sup>(7)</sup>	10-point LED for 1 <sup>st</sup> control output, 0...100%
LEDs	8 (6 for 'S') control LEDs
Keyboard	5 (4 for 'S') membrane keys
Operating conditions	
Ambient temperature	0...50 °C
Ambient humidity	20...85 %RH
Storage temperature	-20...65 °C
Storage humidity	0...95 %RH, non-condensing
Design and materials	
	'B' 'H' / 'V' 'Q' 'S'
Front dimensions [mm]	96x96 96x48 72x72 48x48
Mounting	panel panel panel panel
Panel cutout [mm]	91x91 91x45 69x69 45x45
Mounting depth [mm]	81 81 81 81
PV display digit height [mm]	14 8 14 8
SV display digit height [mm]	10 8 10 8
Maximum weight [g]	300 225 225 150
Protection, front/terminals	IP56/20 IP56/20 IP56/20 IP56/20
Increased front IP (option)	IP65 IP65 IP65 -
Case material	plastic plastic plastic plastic
Wiring (terminals)	screw screw screw screw

**Ordering code** RT1800 - G0.G5'G5'.G5"G5"G5".G8.G9'9".G11 - #1.#2.#3

Code	Feature or option	Code values
<b>G0</b>	Case (front size)	<b>B</b> - 96x96 mm, <b>H</b> - 96x48 mm, <b>V</b> - 48x96 mm, <b>Q</b> - 72x72 mm, <b>S</b> - 48x48 mm
<b>G5'</b>	Relay control output <sup>(3)</sup>	<b>X</b> - none, <b>C</b> - relay NO/NC <sup>(4)</sup> , <b>D</b> - SSR <sup>(5)</sup> , <b>J</b> - for external SSR, <b>M</b> - isolated MOS gate <sup>(5)</sup>
<b>G5"</b>	Relay alarm output <sup>(3)</sup>	<b>X</b> - none, <b>C</b> - relay NO/NC <sup>(4)</sup> , <b>D</b> - SSR <sup>(5)</sup> , <b>J</b> - for external SSR, <b>M</b> - isolated MOS gate <sup>(5)</sup>
<b>G8</b>	Control algorithm	<b>F</b> - PID-fuzzy (ON/OFF), <b>H</b> - PID-fuzzy plus pattern control
<b>G9'</b>	Serial interface <sup>(9)</sup>	<b>X</b> - none, <b>A</b> - RS232, <b>B</b> - RS485
<b>G9"</b>	Protocol	<b>M</b> - MODBUS (ASCII), <b>N</b> - MODBUS (RTU)
<b>G11</b>	Analog control output <sup>(6)</sup>	<b>X</b> - none, <b>E</b> - 0...20 mA, <b>F</b> - 4...20 mA, <b>K</b> - 0...10 V
<b>#1</b>	Auxiliary input <sup>(2)</sup>	<b>X</b> - none, <b>E</b> - 0...20 mA, <b>F</b> - 4...20 mA
<b>#2</b>	Analog retransmission output <sup>(8)</sup>	<b>X</b> - none, <b>E</b> - 0...20 mA, <b>F</b> - 4...20 mA, <b>K</b> - 0...10 V
<b>#3</b>	Increased front protection	<b>X</b> - none, <b>P</b> - IP65 front protection <sup>(7)</sup>